

# LED UP TIMER

## MM:SS Format



### NEMA 1 HOUSED (LIGHT INDUSTRIAL)



#### FEATURES/OPERATION

- ✓ START, STOP, RESET OPERATION
- ✓ BUILT-IN PUSHBUTTON CONTROL
- ✓ 4.0 INCH DIGIT - 200 FOOT VIEW
- ✓ MEMORY BACKUP VALUE DURING POWER LOSS
- ✓ INDUSTRIAL HOUSED (N1)
- ✓ INDOOR BRIGHT RED L.E.D.

DESCRIPTION	PART #
4.0" 4 Digit Timer, NEMA 1, 1 Sided, 17"x7"x3.5"	TL-2451-907

SPECIFICATIONS	
LED:	4.0 Inch, 4 Digit, RED, Solid Seven Seg.
Viewing:	Up to 200 Feet
Max. Time:	99:59 MM:SS Operation
Connection:	Pushbuttons on end of unit
Operation:	Time Up
Logic Inputs:	24VDC / 120VAC (no 24V supply)
Inputs:	Start, Stop, Reset - Momentary
Power:	120VAC @ less than 1 amp
LED Life:	100,000 Hours (11.4 years)
Housing:	NEMA1 Industrial Black Aluminum
Dimensions:	17" wide by 7" tall by 3.125" deep
Memory:	Backup last value up to 1 week

The Trimline Event Timer with pushbutton start, stop, reset is designed to be a versatile solution for most manual production timing applications.

Four inch four digit RED numeric display timer. NEMA1 black aluminum housing with pushbuttons mounted to side of unit. Power is 110 Vac at 1 amp. Includes three pushbutton switches for start/stop/reset, and labels.

Preset dip switch for setting value. If dip switch is set for all zero, firmware will operate timer as a time up timer. If dip switch has any value settings other than zero, firmware will operate timer as a time down timer with dip switch preset values.

\*Dip switch is located inside the unit and requires removing end plate of unit to access. This unit is only to be used for presets that do not change often (i.e. every day/month,etc.).

#### MANUAL # PB-2149-410

**Need something custom?**  
Call us with your specifications  
for a quote on a custom solution.



**Phone: 614-851-1100**

American LED-gible Inc.

1776 Lone Eagle Street Columbus, Ohio 43228

Phone: 614-851-1100 Fax: 614-851-1121

[www.ledgible.com](http://www.ledgible.com)

[www.ledandon.com](http://www.ledandon.com)